

STEP 1

REMOTE ACCOUNT

A. Login

Begin your Remote Experience by using a PC running on the same local network as your Controller, and then pointing your web browser to <http://myremotemanager.com>. Please note that you must be using at least Internet Explorer 5.5, FireFox 1.0, or Safari 1.0.

Enter the **User ID** and **Password**, you created when you purchased the system, in the appropriate fields and log in to your account.

B. Password Help

Once logged into your account, navigate to the **'ACCOUNT SETTINGS'**, then go to the **General Settings Box**, and input your new password in the appropriate two fields. When complete click on the **'SUBMIT'** button.

C. Using Quick-Arm Buttons/Rules

If you would like to use the quick **'ARM/DISARM'** buttons on the top of the **Device List** page or set up **Rules** through the **Security Wizard** to control your Alarm Panel, you must enter a **USER CODE** for the system in the **User Code** field on the **Virtual Keypad** pop-up.

Until this step is completed the XG1000 Controller will NOT be able to arm/disarm the panel as part of a Rule/Schedule or through the quick **'ARM/DISARM'** buttons at the top of the **Device List** page.

You can also create custom device-based **Rules** by clicking on the **'SECURITY & ALERTS'** tab and following the WIZARD or timer-based **Rules** by clicking on the **'TIMERS'** tab. For example, you can have a light automatically turn on when your Alarm Panel is Armed or you could set your Alarm Panel to Arm/Disarm automatically at pre-determined times.

STEP 2

VIRTUAL KEYPAD

Click the **Device Overview** tab to access the Device List for the system. Once you are at the **Device List**, click on the **Settings** icon for your **Honeywell, DSC, or DMP Alarm Panel** to access your Virtual Keypad.

From your Virtual Keypad you may manually enter a user code to Arm or Disarm your Alarm Panel.

Choose up to 5 email/SMS **Alarm Notification Addresses** (if the address does not already appear in the list, click on the **'ADD NEW'** button) that you would like to receive Alarm Notifications when your Alarm Panel is Armed, Disarmed, or goes into Alarm Mode.

You can also select any camera you would like to exclude from capturing video in the event of an **Alarm Condition**. Click on the **'APPLY CHANGES'** button to save your settings.

STEP 3

VIEW LIVE VIDEO

For each of your discovered cameras, you will see a **Snapshot** of the view associated with the camera. Click on the triangular **'PLAY'** button next to the **'REFRESH'** button and the live video will play in-place on the **Snapshot** screen. This will allow you to view a number of webcams right on the **Live Video** page.

If you need the controls for the webcam, click any area of the image to open the pop-up live video window. You must turn off the live video first, though, by clicking on the square **'STOP'** button.

The first time you access your Live Video you may be prompted with a pop up window to install a Java (Safari or Firefox) or ActiveX (Internet Explorer) Plug-In.

This plug-in is necessary to view your live video.

The appearance of the plug-in installer will differ for the two plug-ins, but in both cases you must click **'YES'** to accept the download for the plug-in. Follow the instructions provided in the INSTALLATION WIZARD for the plug-in. The plug-in will take a few minutes to install.